B Series Antenna Amplifiers

BA-03 BB-21

Use:

- B series antenna amplifiers are suitable for boost of weak TV signal

Features:

- High max.output level.It is suitable for multi-channel reception.
- Use plastic housing for outdoor water-proof.
- It is capable to remote feed power(+12V, 60mA)for former amplifier

Specifications:

Model	BA-03(Indoor)		BB-21(Outdoor)	
Freq range(MHz)	45-230	470-860	45-230	470-860
Gain(dB)	20±1	30±2	30±1	40±2
Max.output level (dBμv)①	112	114	112	114
Flatness(dB)	±1	±2	±1	±2
Manual gain control(dB)	0--6	0--6	0--6	0--6
Noise figure(dBMax.)	6	6	6	6
Return loss(dBMin.)	8	6	8	6
Power consumption	10VA			
Power supply	AC 220V±10%		AC 16V Remote supply	

Note: ①Test by DIN45004B

TEL:65-62812711 62812611 FAX:65-63822833 http://www.aph.com.sg http://www.aph-trading.com