

DVB-T Digital Terrestrial Receiver for Mobile



APH Household T1008SPLUS Notable Character:

- ✦ Fully MPEG II / DVB-T compliant
- ✦ 7 MHz, 8 MHz automatic software settings
- ✦ EPG display and overview the program form for the next 64 days
- ✦ OSD Multi-language menu
- ✦ 2500 editable TV channels and 1000 editable radio channels
- ✦ PAL / NTSC automatic conversion
- ✦ OSD Teletext (page cache for 3000 pages)
- ✦ Channel list editor (Copy, move and delete operations available)
- ✦ Channel automatic scan
- ✦ Digital Audio SPDIF output (PCM / AC3 / DTS)
- ✦ Games, calendar
- ✦ Software update through RS-232 port
- ✦ RF loop output
- ✦ DC 6.5 - 28V power supply
- ✦ T1008SPLUS in vehicles, extreme small size, suitable for acoustics expanded slots in vehicles
- ✦ Receiving the signals even when driving in high speed
- ✦ Strongly resist interrupt transmitted in many ways
- ✦ Software update port

SPECIFICATIONS

Input level -----	-65dBm ~ -8dBm	Packing size (mm) Gift box 400*345*80(A) 365*315*80(B) 335*300*80(C) 300*260*60(D) 395*275*70(E) 260*165*62(F)
Input frequency range ----	49 ~ 870 MHz	
Power Supply -----	DC 6.5 ~ 28V	
Power expand -----	15W max	
32Bit RISC CPU -----	@ 130MHz	
Guard Internal Modi -----	1/32, 1/16, 1/8, 1/4	
FEC -----	1/2, 2/3, 3/4, 5/6, 7/8	
Demodulation -----	COFDM 2K/8K - Carrier	